

ROSALEE PHOSEAL BLACK

> Scope

Are you looking forward to a very quick drying eggshell finish black, mostly for interior use and which should offer very tough adhesion to steel as well as to aluminium? Besides, it should be cheaper than N.C. Matt black.

The right answer is rosalee phoseal black. The name stands for phosphate as well as sealing the phosphate film in black shade in one operation only. It is recommended for interior use only through the phosphate film provides adequate corrosion protection.

Areas of Application

Any metallic surface that needs very quick drying, eggshell black finish, mostly for interior. Examples: electric switches, meter boxes, zintec castings, slotted angles, table lamp stands & shades, computer furniture etc.

> Surface Preparation

Essentially, the surface must be free from grease and oil. Solvent wiping can easily do this. If there is light rust, the same will be taken care of by the phosphoric acid constituent in phoseal. It can be applied directly on aluminium or zintec and for which there is no need to use synthetic primer zinc chromate or wash primer. The only limitation is, film build. Phoseal film cannot give more than 15 microns of dry film thickness.

Technical Data

• APPEARANCE : Thin black liquid

VISCOSITY : 15-16 seconds in ford cup 4 at 30° c.
 SPRAYING VISCOSITY : As it is. Not recommended for brushing.

• DRYING TIME : Touch dry : 5 minutes

Dust free : 10 minutes
Thumb impression free : 15 minutes

Hard dry : 30 minutes

DRY FILM THICKNESS : 15-16 microns
 GLOSS : Eggshell

• SCRATCH HARDNESS : 1000 gms. After 24 hours

• CROSS HATCH TEST : Passes

• FLEXIBILITY : 1/16" bending mandrel

• PETROL & OIL RESISTANCE: Very good



ROSALEE PHOSEAL BLACK

Directions for Use

Prepare the surface as stated and start spraying. The pressure should be within 55-65 psi for getting smooth and even finish.

> Notes

Phoseal can also be stoved at 120°c for 10 minutes to attain very good hard film in a short period. It can also be used by dipping.

Disclaimer

The information contained within this data sheet is based on information believed to be reliable at the time of its preparation. The company will not be liable for loss or damage howsoever caused including liability for negligence which may be suffered by the user of the data contained herein. It is the users' responsibility to conduct all necessary tests to confirm the suitability of any product or system for their intended use. No guarantee of results is implied since conditions of use are beyond our control.